

# High band/VHF FM power transistor

# **MRF243**

### **Description:**

MRF243 is designed as 12.5V, 130-175MHz, high band/VHF FM transistors.

#### Features:

Specified 12.5 V, 160 MHz Performance: Output Power = 60 Watts Power Gain = 7.0 dB Min Efficiency = 55% Min

# **Maximum Ratings**

Rating	Symbol	Value	Unit
Collector-Emitter Voltage	Vceo	18	Vdc
Collector-Base Voltage	Vcbo	36	Vdc
Emitter-Base Voltage	Vebo	4.0	Vdc
Collector Current Continuous	lc	15	Adc
Total Device Dissipation@Tc=25C	Pd	175	W
Max Current gain	hFE	150	

# Drawings:

