High band/VHF FM power transistor

MRF245

Description:

MRF245 is designed as 12.5V, 136-176MHz, high band/VHF FM transistors.


Features:


Specified 12.5 V, 145MHz Performance: Output Power = 80 Watts Power Gain = 6.4 dB Min Efficiency = 55% Min

Maximum Ratings

| Rating | Symbol | Value | Unit |
|---------------------------------|--------|-------|------|
| Collector-Emitter Voltage | Vceo | 18 | Vdc |
| Collector-Base Voltage | Vcbo | 36 | Vdc |
| Emitter-Base Voltage | Vebo | 4.0 | Vdc |
| Collector Current Continuous | Ic | 20 | Adc |
| Total Device Dissipation@Tc=25C | Pd | 250 | W |
| Max Current gain | hFE | 150 | |

Drawings:





SOT119